



## CBU 100W dimmer Casambi



The dimmer is a high quality trailing edge phase dimmer for dimmable resistive and capacitive high voltage loads. Do not use the LED dimmer for fluorescent lamps, fans or ring core transformers. It controls individual luminaires in the Bluetooth Low Energy Mesh network without the use of gateways, routers, repeaters or extra cabling. The dimmer can be used for a maximum of 0.65 A mains current incl. reactive current. Configuration is wireless via the Casambi App. The installation must only be carried out by a qualified electrician.

ELECTRICAL DATA	
Protection Class (system)	2
Dimming (system)	Casambi
Voltage (system) [V]	230V 50Hz
Frequency (Hz)	50/60Hz
Standby (W)	100.0

TECHNICAL DATA	
IP (system)	IP20
Last Level	Yes



TECHNICAL DATA	
Overheat Protection	Yes, Automatically
Soft Start	Yes

DIMENSIONS	
Length (product) (mm)	40.4
Width (product) (mm)	14.0
Height (product) (mm)	36.3
Cable Dimension	0,75-1,5 mm <sup>2</sup>

MATERIALS AND SURFACES	
Color	White

INSTALLATION AND CONNECTION	
Mounting	Recessed
Mounting Dimmer	Electrical box

## WIRING

