



## PRODUCT SHEET

Driver DALI 400mA max 20W 20-50V (one4all) 18i5 DALI/EPN0034

Art. no: 0300-14



*Lighting Solutions*

# Driver DALI 400mA max 20W 20-50V (one4all) 18i5 DA

Tridonic DALI driver preset at 400mA, max 20W.

Primary side 0,3m cable with 18i5 DALI (male).

Secondary side EPN0034 (female).



### SPECIFICATIONS

System Power [W]:	20W
Dimming:	CLO, Corridor, DALI2, Push, Ready2Mains
CC or CV:	CC
CC [mA]:	400 - mA
CC (forward voltage driver) [V]:	20 - 50V
Max output voltage [V]:	60
Output Current Tolerance [%]:	3%
Current Ripple [%]:	2,5%
Current setting:	DALI-2, I-Select 2 Plug (Tridonic), Ready2Ma
Expected Lifetime:	100000h
System Voltage [V]:	230V 50Hz V
Protection Class:	1 or 2
Max load pr circuit - B10:	19
Max load pr circuit - B16:	32
Max load pr circuit - C10:	31
Max load pr circuit - C16:	53
Leakage current [mA]:	0,15mA
Inrush current I <sub>max</sub> [A]:	26A
Inrush current time [μs]:	151μs
Manufacture:	Tridonic
Primary Connection:	18i5 DALI male
Secondary Connection:	EPN0034 female
Length:	210mm
Height:	30mm
Width:	43mm
Weight:	0,14kg