



PRODUCT SHEET

Driver DALI 350mA max 17W 15-49V (one4all) 18i5 DALI/EPN0034

Art. no: 0300-13



Lighting Solutions

Driver DALI 350mA max 17W 15-49V (one4all) 18i5 DALI

Tridonic DALI driver preset at 350mA, max 17W.

Primary side 0,3m cable with 18i5 DALI (male).

Secondary side EPN0034 (female).



SPECIFICATIONS

System Power [W]:	17W
Dimming:	CLO, Corridor, DALI2, Push, Ready2Mains
CC or CV:	CC
CC [mA]:	350 - mA
CC (forward voltage driver) [V]:	15 - 49V
Max output voltage [V]:	60
Output Current Tolerance [%]:	3%
Current Ripple [%]:	5%
Current setting:	DALI-2, I-Select 2 Plug (Tridonic), Ready2Ma
Expected Lifetime:	100000h
System Voltage [V]:	230V 50Hz V
Protection Class:	1 or 2
Max load pr circuit - B10:	21
Max load pr circuit - B16:	35
Max load pr circuit - C10:	40
Max load pr circuit - C16:	64
Leakage current [mA]:	0,7mA
Inrush current I _{max} [A]:	20A
Inrush current time [μs]:	140μs
Manufacture:	Tridonic
Primary Connection:	18i5 DALI male
Secondary Connection:	EPN0034 female
Length:	210mm
Height:	30mm
Width:	43mm
Weight:	0,14kg