



## PRODUCT SHEET

Driver DALI 700mA max 35W 25-50V (one4all) 18i5 DALI/EPN0034

Art. no: 0300-17



*Lighting Solutions*

# Driver DALI 700mA max 35W 25-50V (one4all) 18i5 DAL

Tridonic DALI driver preset at 700mA, max 35W.

Primary side 0,3m cable with 18i5 DALI (male).

Secondary side EPN0034 (female).



### SPECIFICATIONS

System Power [W]:	35W
Dimming:	CLO, Corridor, DALI2, Push, Ready2Mains
CC or CV:	CC
CC [mA]:	700 - mA
CC (forward voltage driver) [V]:	25 - 50V
Max output voltage [V]:	60
Output Current Tolerance [%]:	3%
Current Ripple [%]:	2%
Current setting:	DALI-2, I-Select 2 Plug (Tridonic), Ready2Ma
Expected Lifetime:	100000h
System Voltage [V]:	230V 50Hz V
Protection Class:	1 or 2
Max load pr circuit - B10:	14
Max load pr circuit - B16:	23
Max load pr circuit - C10:	23
Max load pr circuit - C16:	38
Leakage current [mA]:	0,16mA
Inrush current I <sub>max</sub> [A]:	23A
Inrush current time [μs]:	200μs
Manufacture:	Tridonic
Primary Connection:	18i5 DALI male
Secondary Connection:	EPN0034 female
Length:	210mm
Height:	30mm
Width:	43mm
Weight:	0,14kg