




PRODUCT FAMILY SHEET

Alcor 12V



Lighting Solutions



Alcor 12V

This furniture downlights makes it very easy to replace from old halogen fittings with LED technology. Integrated push-in terminals enable to use existing dimmer, transformer and wires. Replaces halogen downlights with hole measurements 57-60mm. Connect to 12V AC/DC, and can be dimmed on AC.

VERSIONS

Art.No	Effect [W]	Cold Lumen [lm]	Lumen Output [lm]	CCT [K]	Beam Angle [°]	Lens Difuser	CRI [>]	Color	Light Control	Connection
2174-70-12	4,6	340	340	2700	70°	Clear	80	rushed Ste	nding on Dr	Terminal
2174-70-3	4	380	380	2700	70°	Clear	80	White	nding on Dr	Terminal