



## PRODUCT SHEET

Driver Dali 700mA 30W Dali 18i5/EPN0034

Art. no: 0300-49



# Driver Dali 700mA 30W Dali 18i5/EPN0034



### SPECIFICATIONS

System Power [W]:	30W
Dimming:	DALI2
Standby power P <sub>sb</sub> (W) <:	0,5
Flicker metric (P <sub>st</sub> LM) <:	1
Stroboscopic effect metric (SVM) <:	0,4
CC or CV:	CC
CV (driver) [V]:	33V
CC [mA]:	300 - 750mA
CC (forward voltage driver) [V]:	6 - 42V
Max output voltage [V]:	42
Output Current Tolerance [%]:	5%
Current Ripple [%]:	5%
Expected Lifetime:	100000h
System Voltage [V]:	230V 50HzV
Protection Class:	2
Dimming Minimum Level :	1%
Dimming output type:	Amplitude Modulation
Max load pr circuit - B10:	48
Max load pr circuit - B16:	77
Max load pr circuit - C10:	48
Max load pr circuit - C16:	77
Leakage current [mA]:	0,7mA
Inrush current I <sub>max</sub> [A]:	6,5A
Inrush current time [μs]:	194μs
Manufacture:	Boke
Primary Connection:	18i5 DALI male
Secondary Connection:	EPN0034 female