



## CBU 460W dimmer Casambi



The AIMOTION dimmer is a high quality trailing edge phase dimmer for dimmable resistive and capacitive high voltage loads. Do not use the LED dimmer for fluorescent lamps, fans or ring core transformers. It controls individual luminaires in the Bluetooth Low Energy Mesh network without the use of gateways, routers, repeaters or extra cabling. The dimmer can be used with loads of up to 460W. Configuration is wireless via the Casambi App. The installation must only be carried out by a qualified electrician.

ELECTRICAL DATA	
Protection Class (system)	2
Dimming (system)	Casambi
Voltage (system) [V]	230V 50Hz
Frequency (Hz)	50/60Hz
Standby (W)	460.0

TECHNICAL DATA	
IP (system)	IP20
Overheat Protection	Yes, Automatically



TECHNICAL DATA	
Soft Start	Yes

DIMENSIONS	
Length (product) (mm)	103.0
Width (product) (mm)	28.0
Height (product) (mm)	35.0
Weight (product) (kg)	0.05

MATERIALS AND SURFACES	
Color	Black

## WIRING

