

**PRODUCT DATA SHEET**

CBU P4 Push Button Interface Casambi

Art.no: 1019-P4

*Lighting Solutions*

## CBU P4 Push Button Interface Casambi



The AIMOTION Pushbutton Module 4 CH communicates wirelessly in the Bluetooth Low Energy Mesh network without the use of gateways, routers, repeaters or extra cabling. The Pushbutton Module is designed so that up to four standard installation pushbuttons with mains voltage can be added to a Casambi network. Alternatively, motion detectors / sensors or other switches can be connected via mains voltage. The connections control e.g. one luminaire, device, group, scene/animation, all luminaires or motion/automation. Configuration is done wirelessly via the Casambi app. The Pushbutton Module has a compact format, suitable for installation in flush-mounted boxes (deep flush-mounted boxes are recommended). Installation may only be carried out by a qualified electrician.

ELECTRICAL DATA	
Protection Class (system)	2
Dimming (system)	Casambi
Voltage (system) [V]	230V 50Hz

TECHNICAL DATA	
IP (system)	IP20
Operating temperature (°C)	0 - 50



**PRODUCT DATA SHEET**  
CBU P4 Push Button Interface Casambi  
Art.no: 1019-P4



*Lighting Solutions*

DIMENSIONS	
Length (product) (mm)	44.0
Width (product) (mm)	16.0
Height (product) (mm)	29.0
Weight (product) (kg)	0.02

MATERIALS AND SURFACES	
Color	Black